



HTNG Intelligent Guest Room Specification Version 3.0

31 October 2014

About HTNG

Hotel Technology Next Generation (HTNG) is a non-profit association with a mission to foster, through collaboration and partnership, the development of next-generation systems and solutions that will enable hoteliers and their technology vendors to do business globally in the 21st century. HTNG is recognized as the leading voice of the global hotel community, articulating the technology requirements of hotel companies of all sizes to the vendor community. HTNG facilitates the development of technology models for hospitality that will foster innovation, improve the guest experience, increase the effectiveness and efficiency of hotels, and create a healthy ecosystem of technology suppliers.

Copyright 2014, Hotel Technology Next Generation

All rights reserved.

No part of this publication may be reproduced, stored in a retrieval system, or transmitted, in any form or by any means, electronic, mechanical, photocopying, recording, or otherwise, without the prior permission of the copyright owner.

For any software code contained within this specification, permission is hereby granted, free-of-charge, to any person obtaining a copy of this specification (the "Software"), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the above copyright notice and this permission notice being included in all copies or substantial portions of the Software.

Manufacturers and software providers shall not claim compliance with portions of the requirements of any HTNG specification or standard, and shall not use the HTNG name or the name of the specification or standard in any statements about their respective product(s) unless the product(s) is (are) certified as compliant to the specification or standard.

THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT. IN NO EVENT SHALL THE AUTHORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES, OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF, OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

Permission is granted for implementers to use the names, labels, etc. contained within the specification. The intent of publication of the specification is to encourage implementations of the specification.

This specification has not been verified for avoidance of possible third-party proprietary rights. In implementing this specification, usual procedures to ensure the respect of possible third-party intellectual property rights should be followed. Visit <http://htng.org/ip-claims> to view third-party claims that have been disclosed to HTNG. HTNG offers no opinion as to whether claims listed on this site may apply to portions of this specification.

The names Hotel Technology Next Generation and HTNG, and logos depicting these names, are trademarks of Hotel Technology Next Generation. Permission is granted for implementers to use the aforementioned names in technical documentation for the purpose of acknowledging the copyright and including the notice required above. All other use of the aforementioned names and logos requires the permission of Hotel Technology Next Generation, either in written form or as explicitly permitted for the organization's members through the current terms and conditions of membership.

Table of contents

31 OCTOBER 2014	1
1 THIS SPECIFICATION AT A GLANCE.....	6
2 DOCUMENT INFORMATION	7
2.1 DOCUMENT HISTORY	7
2.2 DOCUMENT PURPOSE	8
2.3 SCOPE	8
2.4 RELATIONSHIP TO OTHER STANDARDS.....	8
2.5 USEFUL RESOURCES.....	9
2.6 AUDIENCE.....	9
2.7 OVERVIEW	9
2.8 KNOWN LIMITATIONS	9
3 COMPONENT SCENARIOS.....	10
3.1 GUEST ROOM STATUS CHECK.....	10
3.1.1 <i>Overview</i>	10
3.1.2 <i>Roles</i>	10
3.1.3 <i>Use Case</i>	10
3.1.4 <i>Message Flows</i>	11
3.1.5 <i>Sample Request</i>	11
3.1.6 <i>Sample Response</i>	12
3.1.7 <i>Sample Request</i>	12
3.1.8 <i>Sample Response</i>	12
3.1.9 <i>Sample Request</i>	13
3.1.10 <i>Sample Response</i>	13
3.2 GUEST ROOM STATUS EVENT NOTIFICATION	15
3.2.1 <i>Overview</i>	15
3.2.2 <i>Roles</i>	15
3.2.3 <i>Use Case</i>	15
3.2.4 <i>Message Flows</i>	16
3.2.5 <i>Sample Request</i>	16
3.2.6 <i>Sample Response</i>	16
3.3 DEVICE REGISTRATION.....	17
3.3.1 <i>Overview</i>	17
3.3.2 <i>Roles</i>	17
3.3.3 <i>Use Case</i>	17
3.3.4 <i>Message Flows</i>	18
3.3.5 <i>Sample Request</i>	18
3.3.6 <i>Sample Response</i>	21
3.4 DEVICE CAPABILITY PROFILE MANAGEMENT	21

3.4.1	Overview	21
3.4.2	Roles	21
3.4.3	Use Case	21
3.4.4	Message Flows	22
3.4.5	Sample Request	22
3.4.6	Sample Response	23
3.5	DEVICE DISCOVERY	24
3.5.1	Overview	24
3.5.2	Roles	24
3.5.3	Use Case	24
3.5.4	Message Flows	25
3.5.5	Sample Request	25
3.5.6	Sample Response	25
3.6	INTERACTING WITH DEVICES – COMMAND	26
3.6.1	Overview	26
3.6.2	Roles	26
3.6.3	Use Case	26
3.6.4	Message Flows	27
3.6.5	Sample Request – Turning on a lamp	27
3.6.6	Sample Response	27
3.7	INTERACTING WITH DEVICES – STATUS	28
3.7.1	Overview	28
3.7.2	Roles	28
3.7.3	Use Case	28
3.7.4	Message Flows	29
3.7.5	Sample Request	29
3.7.6	Sample Response	29
3.8	INTERACTING WITH DEVICES – EVENT	30
3.8.1	Overview	30
3.8.2	Roles	30
3.8.3	Use Case	30
3.8.4	Message Flows	31
3.8.5	Sample Request	31
3.8.6	Sample Response	31
4	MESSAGES	32
4.1	GUEST ROOM STATUS CHECK	32
4.1.1	Data Element Table – Request	32
4.1.2	Data Element Table – Response	34
4.2	GUEST ROOM STATUS EVENT NOTIFICATION	37
4.2.1	Data Element Table – Request	37
4.2.2	Data Element Table – Response	39

4.3	DEVICE REGISTRATION	41
4.3.1	<i>Data Element Table - Request</i>	41
4.3.2	<i>Data Element Table - Response</i>	46
4.4	DEVICE CAPABILITY PROFILE MANAGEMENT	48
4.4.1	<i>Data Element Table - Request</i>	48
4.4.2	<i>Data Element Table - Response</i>	52
4.5	DEVICE ENDPOINT DISCOVERY	54
4.5.1	<i>Data Element Table - Request</i>	54
4.5.2	<i>Data Element Table - Response</i>	56
4.6	INTERACTING WITH DEVICES - COMMAND	61
4.6.1	<i>Data Element Table - Request</i>	61
4.6.2	<i>Data Element Table - Response</i>	63
4.7	INTERACTING WITH DEVICES - STATUS	65
4.7.1	<i>Data Element Table - Request</i>	65
4.7.2	<i>Data Element Table - Response</i>	67
4.8	INTERACTING WITH DEVICES - EVENT	69
4.8.1	<i>Data Element Table - Request</i>	69
4.8.2	<i>Data Element Table - Response</i>	72
5	APPENDICES	74
5.1	GLOSSARY OF TERMS	74
5.2	REFERENCED DOCUMENTS	75

1 This Specification at a Glance

This specification is used by hotel information systems to determine the operational status or health of guest room devices. Described are message exchange patterns that make it possible to request the status of guest room devices (ad-hoc query) and register to receive notification messages (status change events) when the health of devices in a guest room change, as well as messages for registering and discovering devices.

This Intelligent Guest Room specification is the bridge between the [HTNG Guest & Room Messaging Status \(GRSM\) specification](#) and the [HTNG Device Messaging Structure \(DMS\) specification](#). The GRSM specification is a high-level, guest stay-related informational messaging, whereas the DMS specification is a low-level device protocol.

2 Document Information

2.1 Document History

Version	Date	Author	Comments
1.0	19 Oct 2012	Intelligent Guest Room (IGR) Workgroup	Released spec – addressed Guest Room Status Check and Guest Room Status Event Notification use cases
1.01	28 Oct 2012	IGR Workgroup	Added Registration and Discovery scenarios
1.02	12 Dec 2012	IGR Workgroup	Updated Sections 1, 2 & 5
1.03– 1.08	09 Jan 2013 – 13 Mar 2013	IGR Workgroup	Updated sample messages
1.90	21 Mar 2013	Kylene Reese	Prepared for member review period
1.95	10 Apr 2013	Kylene Reese	Prepared spec for Workgroup vote
2.0	19 Apr 2013	IGR Workgroup	Release spec – includes centralized registration and discovery of in-room devices
2.01	13 Mar 2014	Kylene Reese	Prepared doc for workgroup discussion and added use cases
2.02	19 Mar 2014	IGR Workgroup	Finalized Interacting with Devices scenarios
2.03	2 Apr 2014	IGR Workgroup	Began identifying data elements.
2.04	22 Apr 2014	Jay Rosamilia	Added sample messages for Command, Status and Event
2.05	23 Apr 2014	IGR Workgroup	Continued updating sample messages
2.06–.08	10 Jun 2014	Jay Rosamilia	Completed Data Element Tables for Command and Control
2.09	16 Jul 2014	IGR Workgroup	Reviewed Jay’s work

2.2 Document Purpose

More and more, hoteliers are expected to provide guests with all the technology, connectivity and devices that they are used to experiencing in their home environment. Advanced in-room technologies have become a requirement rather than a luxury. But creating that at-home experience is much more difficult for hoteliers than it is for their tech-savvy guests. For the consumer, installing devices and connecting systems is a simple, straight-forward process. However, hoteliers must face the challenge of implementing and maintaining an on-property infrastructure that supports in-room devices and gives all their guests the at-home experience they expect. This specification provides hoteliers with web services that facilitate the deployment and management of their in-room technology infrastructure.

2.3 Scope

This document targets the release of a specification providing the necessary components, including design recommendations, WSDLs, XSDs and scenarios allowing a hospitality operator or hospitality system provider to design and deploy a set of device-based services in-line with best practices, methods and procedures that meet or exceed current industry web services standards specifications. Basic functionality of the Intelligent Guest Room services makes it possible to remotely monitor the status of devices in a room. This specification addresses the ability to remotely query the current and last status of a device or group of devices and subscribe to device status change notifications as well as the ability to register and discover devices.

2.4 Relationship to Other Standards

This Intelligent Guest Room specification is the bridge between the [HTNG Guest & Room Messaging Status \(GRSM\) specification](#) and the [HTNG Device Messaging Structure \(DMS\) specification](#). The GRSM specification is a high-level, guest stay-related informational messaging, whereas the DMS specification is a low-level device protocol.

This specification and its supporting schemas leverage the existing OpenTravel Alliance methodology for message construction and incorporate a sub set of applicable [OpenTravel Alliance specifications](#). This ensures a consistent representation of data across the various HTNG specifications.

The [HTNG Web Services Framework Technical Specification](#) provides information on the population of the SOAP Header and the transport of messages.

Please refer to the [HTNG Event Notification Specification](#) for details on how to subscribe to and manage notifications defined in this specification.

2.5 Useful Resources

- [Implementing Web Services Using HTNG Specifications – A Quick Start Guide for Software Developers](#)
- HTNG Discussion Board – currently available at <http://www2.htng.org/discussion>

2.6 Audience

This document is intended to aid in the design, integration and deployment of hospitality systems that require interaction with in-room devices in order to monitor room-based technologies. The document specifically targets hospitality systems developers, integrators and operators.

2.7 Overview

Content contained in this document is intended to assist in the design, implementation and integration of a set of applications and services whose feature set is based on the status of in-room device technologies. A brief overview of each section is as follows:

Section 3 – Scenarios

This section includes the scenario overviews, diagrams, roles, use cases, data element tables and sample messages. The technical artifacts (XSDs and WSDLs) for this certification release of IGR v3.0 can be found in a separate ZIP file included with specification.

Section 4 – Messages

Detailed Data Element tables and sample messages are provided in this section.

Section 5 – Appendices

This section includes terms, implementation requirements, links, any referenced documents, as well as common HTNG schema components referenced in this document.

2.8 Known Limitations

There are no known limitations of this specification at the time of release.

3 Component Scenarios

The Intelligent Guest Room (IGR) system is a set of standards that make it possible to enhance the guest experience through the use of integrated guest room device technologies. The IGR system encompasses a set of web service standards that make it possible to obtain information from intelligent guest room devices. Using this IGR specification, vendors and/or hoteliers are able to acquire information about the operational status of devices in a guest room in order to minimize guest impact when guest room technology-related problems arise.

It is recommended that both the sending and receiving systems log all inbound and outbound communications to facilitate troubleshooting.

From an application security standpoint, it is up to trading partners to ensure the requesting system has authority to perform the requested functions. It is up to the receiving system to enforce application security, which is important, although out-of-scope of this specification.

3.1 Guest Room Status Check

3.1.1 Overview

In order to enhance the guest experience, a Hotel Information System is required to check the status of guest room technologies prior to room assignment. This may be completed at check-in, pre-arrival or even during the stay. The goal of the status check is to ensure that guest room technologies are functioning properly.

3.1.2 Roles


Role	Description	Examples
Hotel Information System	Any hotel software application or service containing features sets based on the status of guest room devices.	<ul style="list-style-type: none">• PMS• Work order management• Device management console
Intelligent Guest Room (IGR) System	A system that provides the ability to query the status of guest room devices.	<ul style="list-style-type: none">• Device Gateway• Zone Controller

3.1.3 Use Case

Assumption:	IGR System is fully functional and accessible.
Pre-conditions:	None
Trigger:	Request for room status.

Basic Course of Events:	<ol style="list-style-type: none"> 1) The Hotel Information System constructs an appropriate request message and sends a status check request to the IGR System. 2) The IGR System enumerates guest room devices in order to determine their operational status. 3) The IGR System returns the operational status to the Hotel Information System.
Post-condition:	Hotel Information System knows the room device status.
Exception Paths:	<ul style="list-style-type: none"> • IGR System returns an error status indicating one or more devices are not functioning properly. The error status message includes a severity indicator used by the requesting Hotel Information system to determine a course of action. • Failure of IGR System to return a response.
Alternative Path:	None

3.1.4 Message Flows



3.1.5 Sample Request

```

<HTNG_HotelRoomStatusSearchRQ EchoToken="Echo12345" Timestamp="2012-08-17T09:30:47Z"
Version="1.0">
  <POS>
    <Source>
      <RequestorID Type="10" ID_Context="ACME_PMS" ID="PMS1">
        <CompanyName>Acme PMS Company</CompanyName>
      </RequestorID>
    </Source>
  </POS>
  <PropertyInfo ChainCode="Hotel Chain" BrandCode="Hotel Brand" HotelCode="Hotel Hotel"/>
  <Room RoomID="EE12345">
    <Devices>
      <Device Type="TV Remote" FriendlyName="000" Class="TelevisionIntegration"/>
      <Device Type="Television" FriendlyName="TV-1" Class="TelevisionIntegration"/>
      <Device Type="Thermostat" Class="HVAC"/>
      <Device Class="DoorLock"/>
    </Devices>
  </Room>
</HTNG_HotelRoomStatusSearchRQ>

```

3.1.6 Sample Response

```
<HTNG_HotelRoomStatusSearchRS EchoToken="Echo12345" Timestamp="2012-08-17T09:30:47Z"
Version="1.0">
  <Success/>
  <RoomInformationList>
    <RoomInformation>
      <Room RoomID="EE12345">
        <Devices>
          <Device ID="1129087f" FriendlyName="RMF01" Type="TVRemote" Description="Acme television
remote control" Class="TelevisionIntegration">
            <CurrentHealthStatus Value="WARNING" Reason="LOW_BATTERY"/>
          </Device>
          <Device ID="ef29086f" FriendlyName="TV-1" Type="Television" Description="Acme 52 inch
Hospitality TV - Bedroom" Class="TelevisionIntegration">
            <CurrentHealthStatus Value="OPERATIONAL"/>
          </Device>
          <Device ID="ac3f196e-2a3b-23af-2bbe-2e67998e1e88" FriendlyName="Tstat-R1"
Type="Thermostat" Description="Room Thermostat" Class="HVAC">
            <CurrentHealthStatus Value="WARNING" Reason="PARTIAL_FAILURE">An attempt to test the
temperature sensor status failed. Device returned error 1101.</CurrentHealthStatus>
          </Device>
          <Device ID="bf3f195a" FriendlyName="DL-12345" Description="Door Lock" Class="DoorLock">
            <CurrentHealthStatus Value="ERROR" Reason="COMMUNICATION_ERROR">An attempt to test
the door lock status failed. Lock Server Offline. Error 502.</CurrentHealthStatus>
          </Device>
        </Devices>
      </Room>
    </RoomInformation>
  </RoomInformationList>
</HTNG_HotelRoomStatusSearchRS>
```

3.1.7 Sample Request

```
<HTNG_HotelRoomStatusSearchRQ EchoToken="Echo12345" Timestamp="2012-08-17T09:30:47Z"
Version="1.0">
  <POS>
    <Source>
      <RequestorID Type="10" ID_Context="ACME_PMS" ID="PMS1">
        <CompanyName>Acme PMS Company</CompanyName>
      </RequestorID>
    </Source>
  </POS>
  <PropertyInfo ChainCode="Hotel Chain" BrandCode="Hotel Brand" HotelCode="Hotel Hotel"/>
  <Rooms>
    <Room RoomID="EE12345"/>
  </Rooms>
</HTNG_HotelRoomStatusSearchRQ>
```

3.1.8 Sample Response

```
<HTNG_HotelRoomStatusSearchRS TransactionIdentifier="Tran0001" EchoToken="Echo12345"
Timestamp="2012-08-17T09:30:47Z" Version="1.0">
  <Success/>
  <Warnings>
    <Warning Type="101" Status="OK" ShortText="IGR Reset">IGR services restarted - 2012-08-
10T014:00:47Z</Warning>
  </Warnings>
  <RoomInformationList>
    <RoomInformation>
      <Room RoomID="EE12345">
        <Devices>
          <Device ID="ef29086f" FriendlyName="TV-1" Type="Television" Description="Acme 52 inch
Hospitality TV" Class="TelevisionIntegration">
            <CurrentHealthStatus Value="OPERATIONAL"/>
          </Device>
          <Device ID="af39085e" FriendlyName="STB-001" Type="Set Top Box" Description="Acme Set
Top Box Model m7789K" Class="TelevisionIntegration">
            <CurrentHealthStatus Value="OPERATIONAL"/>
          </Device>
          <Device ID="1129087f" FriendlyName="RMF01" Type="TVRemote" Description="Acme television
remote control" Class="TelevisionIntegration">
            <CurrentHealthStatus Value="OPERATIONAL"/>
          </Device>
        </Devices>
      </RoomInformation>
    </RoomInformationList>
  </RoomInformationList>
</HTNG_HotelRoomStatusSearchRS>
```

```

    <Device ID="ac3f196e-2a3b-23af-2bbe-2e67998e1e88" FriendlyName="Tstat-R1"
Type="Thermostat" Description="Room Thermostat" Class="HVAC">
    <CurrentHealthStatus Value="OPERATIONAL"/>
  </Device>
  <Device ID="bf3f195a" FriendlyName="DL-12345" Description="Door Lock" Class="DoorLock">
    <CurrentHealthStatus Value="OPERATIONAL"/>
  </Device>
  <Device ID="2341ae3c" FriendlyName="MB-12345" Description="Mini Bar"
Class="InRoomRefreshmentCenter">
    <CurrentHealthStatus Value="WARNING" Reason="SERVICE_REQUIRED">Unable to determine
item count. </CurrentHealthStatus>
  </Device>
  <Device ID="ef3278ea" FriendlyName="OS-12345" Description="Ceiling Sensor"
Class="OccupancyDetection">
    <CurrentHealthStatus Value="ERROR" Reason="OFFLINE">Device is unreachable.
Communications error 10060. </CurrentHealthStatus>
  </Device>
</Devices>
<TelephoneExtensions>
  <TelephoneExtension>12345</TelephoneExtension>
</TelephoneExtensions>
</Room>
</RoomInformation>
</RoomInformationList>
</HTNG_HotelRoomStatusSearchRS>

```

3.1.9 Sample Request

```

<HTNG_HotelRoomStatusSearchRQ EchoToken="Echo12345" TimeStamp="2012-08-17T09:30:47Z"
Version="1.0">
  <POS>
    <Source>
      <RequestorID Type="10" ID_Context="ACME_PMS" ID="PMS1">
        <CompanyName>Acme PMS Company</CompanyName>
      </RequestorID>
    </Source>
  </POS>
  <PropertyInfo ChainCode="Hotel Chain" BrandCode="Hotel Brand" Hotel Code="Hotel Hotel"/>
  <Room>
    <Devices>
      <Device Type="Television" FriendlyName="TV-1" Class="TelevisionIntegration">
      </Device>
    </Devices>
  </Room>
</HTNG_HotelRoomStatusSearchRQ>

```

3.1.10 Sample Response

```

<HTNG_HotelRoomStatusSearchRS EchoToken="Echo12345" TimeStamp="2012-08-17T09:30:47Z"
Version="1.0">
  <Success/>
  <RoomInformationList>
    <RoomInformation>
      <Room RoomID="EE12345">
        <Devices>
          <Device ID="ae29086f" FriendlyName="TV-1" Type="Television" Description="Acme 52 inch
Hospitality TV - Bedroom" Class="TelevisionIntegration">
            <CurrentHealthStatus Value="OPERATIONAL"/>
          </Device>
        </Devices>
      </Room>
    </RoomInformation>
    <RoomInformation>
      <Room RoomID="EE22345">
        <Devices>
          <Device ID="ef29086e" FriendlyName="TV-1" Type="Television" Description="Acme 52 inch
Hospitality TV - Bedroom" Class="TelevisionIntegration">
            <CurrentHealthStatus Value="OPERATIONAL"/>
          </Device>
        </Devices>
      </Room>
    </RoomInformation>
    <RoomInformation>
      <Room RoomID="EE32345">
        <Devices>
          <Device ID="ff29086a" FriendlyName="TV-1" Description="Acme 52 inch Hospitality TV -
Bedroom" Class="TelevisionIntegration">

```

```
<CurrentHealthStatus Value="OPERATIONAL"/>
  </Device>
</Devices>
</Room>
</RoomInformation>
</RoomInformationList>
</HTNG_HotelRoomStatusSearchRS>
```

3.2 Guest Room Status Event Notification

3.2.1 Overview

In order to enhance the guest experience, the Room Status Publisher monitors the status of guest room devices and raises an event to a Room Status Subscriber when device failures are detected.

Note: Please refer to the HTNG Event Notification specification for details regarding how to subscribe to and manage notifications.


3.2.2 Roles

Role	Description	Examples
Room Status Publisher	A system that provides the ability to register for and publish events relating to the guest room devices.	<ul style="list-style-type: none">• Device Gateway• Zone Controller
Room Status Subscriber	A system interested in receiving real-time updates to the health and status of guest room devices.	<ul style="list-style-type: none">• PMS• Work order management• Device management console

3.2.3 Use Case

Assumptions:	<ul style="list-style-type: none">• Room Status Publisher is fully functional and accessible.• The Room Status Subscriber is functional and has an active Room Status Publisher event subscription.
Pre-condition:	A Room Status Subscriber has registered interest in receiving event notifications from the Room Status Publisher.
Trigger:	Guest room device failure and corrections.
Basic Course of Events:	As guest room device failures occur or are corrected, the Room Status Publisher detects the status changes and sends an appropriate notification message to registered Room Status Subscribers.
Post-condition:	Hotel staff is informed of guest room device statuses.
Exception Paths:	<ul style="list-style-type: none">• Room Status Publisher returns an error if an attempt to subscribe for notification(s) fails.• Room Status Publisher sends a notification to subscribers when the Room Status Publisher is no longer capable of sending notifications to Room Status Subscribers.
Alternative Path:	None

3.2.4 Message Flows



3.2.5 Sample Request

```
<HTNG_HotelRoomStatusUpdateNotifRQ EchoToken="Echo22222" Timestamp="2012-08-17T09:30:47Z"
Version="1.0">
  <POS>
    <Source>
      <RequestorID Type="10" ID_Context="ACME_PMS" ID="PMS1">
        <CompanyName>Acme</CompanyName>
      </RequestorID>
    </Source>
  </POS>
  <PropertyInfo ChainCode="Hotel Chain" BrandCode="Hotel Brand" Hotel Code="Hotel Hotel" />
  <Room RoomID="EE12345">
    <Devices>
      <Device ID="2341ae3c" FriendlyName="MB-12345" Description="Mini Bar"
Class="InRoomRefreshmentCenter">
        <PriorHealthStatus Value="ERROR" Reason="UNKNOWN"/>
        <CurrentHealthStatus Value="OPERATIONAL" Reason="POWER_CYCLED">Manual device reset
performed</CurrentHealthStatus>
      </Device>
      <Device ID="ef3278ea" FriendlyName="OS-12345" Description="Ceiling Sensor"
Class="OccupancyDetection">
        <PriorHealthStatus Value="ERROR" Reason="LOW_BATTERY"/>
        <CurrentHealthStatus Value="OPERATIONAL" Reason="BATTERY_REPLACEMENT">Device
online.</CurrentHealthStatus>
      </Device>
    </Devices>
  </Room>
</HTNG_HotelRoomStatusUpdateNotifRQ>
```

3.2.6 Sample Response

```
<HTNG_HotelRoomStatusUpdateNotifRS TransactionIdentifier="Tran0002" EchoToken="Echo22222"
Timestamp="2012-08-17T09:30:47Z" Version="1.0">
  <Success/>
</HTNG_HotelRoomStatusUpdateNotifRS>
```

3.3 Device Registration

3.3.1 Overview

Device registration is the process of defining a device and all relevant information to a Device Registration System. Each intelligent device must be registered with the Device Registration System. The registration system provides a means to store device information for the purpose of addressing devices and determining their capabilities and physical location.

3.3.2 Roles


Role	Description	Examples
Device Registration Requester	A system or device capable of publishing device information to be made available to other systems or devices.	<ul style="list-style-type: none"> • Device Gateway • Zone Controller
Device Registration Responder	A repository of references (for the purpose of Addressing) to servers, systems, services and devices and their capabilities.	<ul style="list-style-type: none"> • Device Registration Server

3.3.3 Use Case

Assumptions:	<ul style="list-style-type: none"> • The device to be added has the capability to be addressed via the Device Registration System. • The device end point is uniquely identified. Atomic and hierarchical addresses are allowed. • The address is an URL. • If Device Capability Profiles are being used, the relevant Device Capability Profile has already been established in the Device Registration System. • Registration has been authorized.
Pre-condition:	None
Trigger:	Device is ready to be integrated into the Device Registration System.
Basic Course of Events:	<ol style="list-style-type: none"> 1. A device installer registers the device in the Device Registration System. <ol style="list-style-type: none"> a. A device is added to Device Registration System or an existing device is modified. <ol style="list-style-type: none"> i. If Device Capability Profiles are being used, the appropriate Profile is indicated in the registration request. ii. If Device Capability Profiles are not being used, individual capabilities are included in the message

	<p>payload.</p> <p>b. All pertinent information, including end point address, is added to the Device Registration System.</p>
Post-condition:	Device is registered with the Device Registration System and may be addressed.
Exception Path:	None
Alternative Path:	None

3.3.4 Message Flows



3.3.5 Sample Request

```

<HTNG_DeviceRegistrationRQ EchoToken="TOKEN234" Timestamp="2001-12-17T09:30:47.0Z" Version="1.0">
  <POS>
    <ota:Source>
      <ota:RequestorID Type="0" ID_Context="a" ID="12345678">
        <ota:CompanyName CompanyShortName="a"/>
      </ota:RequestorID>
    </ota:Source>
  </POS>
  <PropertyInfo ChainCode="a" BrandCode="a" HotelCode="a" HotelCodeContext="a"/>
  <Devices>
    <Device Type="LAMP" ID="LMP1234" ModelID="GX-1" SerialNumber="123-SER-789" MACAddress="00-B0-D0-86-BB-F7" FriendlyName="LAMP1234" Description="IGR Lamp" Class="LIGHTING" ModelName="GX-1a">
      <EndpointAddress>http://htng.org/gateway/00-B0-D0-86-BB-F7</EndpointAddress>
      <Manufacturer Type="LAMPMANU" ID_Context="a" ID="a" Instance="a"
URL="http://www.lampco.com">
        <ota:CompanyName CompanyShortName="LAMPCO" Code="LMPCO">LAMPCO Inc. </ota:CompanyName>
      </Manufacturer>
      <DeviceLocation RoomID="1024">
        <RoomType Wing="WEST" Building="A" Floor="10" RoomLocationCode="0"/>
        <TelephoneExtensions>
          <TelephoneExtension>1024</TelephoneExtension>
        </TelephoneExtensions>
      </DeviceLocation>
      <DeviceProfile>
        <Capabilities>
          <Capability Type="STATUS" Operation="getState">
            <OutboundParameters>
              <OutboundParameter DataType="xs:boolean" Property="State">
                <KeyValueItems>
                  <KeyValueItem Key="On" Value="true"/>
                  <KeyValueItem Key="Off" Value="false"/>
                </KeyValueItems>
              </OutboundParameter>
            </OutboundParameters>
          </Capability>
          <Capability Type="COMMAND" Operation="setState">
            <InboundParameters>
              <InboundParameter DataType="xs:boolean" Property="State">
                <KeyValueItems>

```

```
<KeyValueItem Key="On" Value="true"/>
<KeyValueItem Key="Off" Value="false"/>
</KeyValueItems>
</InboundParameter>
</InboundParameters>
<OutboundParameters>
  <OutboundParameter DataType="xs:boolean" Property="RESULT">
    <KeyValueItems>
      <KeyValueItem Key="SUCCESS" Value="true"/>
      <KeyValueItem Key="FAILURE" Value="false"/>
    </KeyValueItems>
  </OutboundParameter>
</OutboundParameters>
</Capability>
<Capability Type="EVENT" Operation="stateChanged">
  <InboundParameters>
    <InboundParameter DataType="xs:boolean" Property="State">
      <KeyValueItems>
        <KeyValueItem Key="On" Value="true"/>
        <KeyValueItem Key="Off" Value="false"/>
      </KeyValueItems>
    </InboundParameter>
  </InboundParameters>
</Capability>
<Capability Type="STATUS" Operation="getDimLevel">
  <OutboundParameters>
    <OutboundParameter DataType="xs:int" Property="DimLevel">
      <KeyValueItems>
        <KeyValueItem Key="Min" Value="0"/>
        <KeyValueItem Key="Max" Value="100"/>
      </KeyValueItems>
    </OutboundParameter>
  </OutboundParameters>
</Capability>
<Capability Type="COMMAND" Operation="setDimLevel">
  <InboundParameters>
    <InboundParameter DataType="xs:int" Property="DimLevel">
      <KeyValueItems>
        <KeyValueItem Key="Min" Value="0"/>
        <KeyValueItem Key="Max" Value="100"/>
      </KeyValueItems>
    </InboundParameter>
  </InboundParameters>
  <OutboundParameters>
    <OutboundParameter DataType="xs:boolean" Property="RESULT">
      <KeyValueItems>
        <KeyValueItem Key="SUCCESS" Value="true"/>
        <KeyValueItem Key="FAILURE" Value="false"/>
      </KeyValueItems>
    </OutboundParameter>
  </OutboundParameters>
</Capability>
<Capability Type="EVENT" Operation="dimLevelChanged">
  <InboundParameters>
    <InboundParameter DataType="xs:int" Property="DimLevel">
      <KeyValueItems>
        <KeyValueItem Key="Min" Value="0"/>
        <KeyValueItem Key="Max" Value="100"/>
      </KeyValueItems>
    </InboundParameter>
  </InboundParameters>
</Capability>
<Capability Type="STATUS" Operation="getScene">
  <OutboundParameters>
    <OutboundParameter DataType="xs:int" Property="Scene">
      <KeyValueItems>
        <KeyValueItem Key="Min" Value="1"/>
        <KeyValueItem Key="Max" Value="32"/>
      </KeyValueItems>
    </OutboundParameter>
  </OutboundParameters>
</Capability>
<Capability Type="COMMAND" Operation="setScene">
  <InboundParameters>
    <InboundParameter DataType="xs:int" Property="Scene">
      <KeyValueItems>
        <KeyValueItem Key="Min" Value="1"/>
        <KeyValueItem Key="Max" Value="32"/>
      </KeyValueItems>
    </InboundParameter>
  </InboundParameters>
</Capability>
```

```
</InboundParameters>
<OutboundParameters>
  <OutboundParameter DataType="xs:boolean" Property="RESULT">
    <KeyValueItems>
      <KeyValueItem Key="SUCCESS" Value="true"/>
      <KeyValueItem Key="FAILURE" Value="false"/>
    </KeyValueItems>
  </OutboundParameter>
</OutboundParameters>
</Capability>
<Capability Type="EVENT" Operation="sceneChanged">
  <InboundParameters>
    <InboundParameter DataType="xs:int" Property="Scene">
      <KeyValueItems>
        <KeyValueItem Key="Min" Value="1"/>
        <KeyValueItem Key="Max" Value="32"/>
      </KeyValueItems>
    </InboundParameter>
  </InboundParameters>
</Capability>
<Capability Type="STATUS" Operation="getGreenMode">
  <OutboundParameters>
    <OutboundParameter DataType="xs:boolean" Property="RESULT">
      <KeyValueItems>
        <KeyValueItem Key="Active" Value="true"/>
        <KeyValueItem Key="Inactive" Value="false"/>
      </KeyValueItems>
    </OutboundParameter>
  </OutboundParameters>
</Capability>
<Capability Type="COMMAND" Operation="setGreenMode">
  <InboundParameters>
    <InboundParameter DataType="xs:boolean" Property="GreenMode">
      <KeyValueItems>
        <KeyValueItem Key="Active" Value="true"/>
        <KeyValueItem Key="Inactive" Value="false"/>
      </KeyValueItems>
    </InboundParameter>
  </InboundParameters>
  <OutboundParameters>
    <OutboundParameter DataType="xs:boolean" Property="RESULT">
      <KeyValueItems>
        <KeyValueItem Key="SUCCESS" Value="true"/>
        <KeyValueItem Key="FAILURE" Value="false"/>
      </KeyValueItems>
    </OutboundParameter>
  </OutboundParameters>
</Capability>
<Capability Type="EVENT" Operation="greenModeChanged">
  <InboundParameters>
    <InboundParameter DataType="xs:boolean" Property="GreenMode">
      <KeyValueItems>
        <KeyValueItem Key="Active" Value="true"/>
        <KeyValueItem Key="Inactive" Value="false"/>
      </KeyValueItems>
    </InboundParameter>
  </InboundParameters>
</Capability>
<Capability Type="STATUS" Operation="getBulbOut">
  <OutboundParameters>
    <OutboundParameter DataType="xs:boolean" Property="BulbOut">
      <KeyValueItems>
        <KeyValueItem Key="Yes" Value="true"/>
        <KeyValueItem Key="No" Value="false"/>
      </KeyValueItems>
    </OutboundParameter>
  </OutboundParameters>
</Capability>
<Capability Type="EVENT" Operation="bulbOutChanged">
  <InboundParameters>
    <InboundParameter DataType="xs:boolean" Property="BulbOut">
      <KeyValueItems>
        <KeyValueItem Key="Yes" Value="true"/>
        <KeyValueItem Key="No" Value="false"/>
      </KeyValueItems>
    </InboundParameter>
  </InboundParameters>
</Capability>
<Capability Type="STATUS" Operation="getUsage">
  <OutboundParameters>
```

```

        <OutboundParameter DataType="xs:int" Property="Usage"/>
    </OutboundParameters>
  </Capability>
</Capabilities>
</DeviceProfile>
</Device>
</Devices>
</HTNG_DeviceRegistrationRQ>

```

3.3.6 Sample Response

```

<HTNG_DeviceRegistrationRS EchoToken="TOKEN234" TimeStamp="2001-12-17T09:30:47.0Z" Version="1.0">
  <Success />
</HTNG_DeviceRegistrationRS>

```

3.4 Device Capability Profile Management

3.4.1 Overview

Device Capability Profiles are used to establish a standard definition for devices that share the same set of capabilities. This reduces the complexity of storing the capabilities of individual devices, and allows a more consistent representation of the devices across the enterprise.


3.4.2 Roles

Role	Description	Examples
Device Registration Requester	A system or device capable of publishing device information to be made available to other systems or devices.	<ul style="list-style-type: none"> Device Gateway Zone Controller
Device Registration Responder	A repository of references (for the purpose of Addressing) to servers, systems, services and devices and their capabilities.	<ul style="list-style-type: none"> Device Registration Server

3.4.3 Use Case

Assumptions:	<ul style="list-style-type: none"> The Device Registration Server is operational. Profile registration has been authorized.
Pre-condition:	None
Trigger:	A device capability profile is ready to be added or modified in the Device Registration Server.
Basic Course of Events:	<ol style="list-style-type: none"> A device installer prepares the Device Capability Profile. A device installer sends the HTNG_DeviceCapabilityProfileRQ to the Device Registration Server.
Post-condition:	The Device Capability Profile is registered with the Device Registration Server and may be used.
Exception Path:	None
Alternative Path:	None

3.4.4 Message Flows



3.4.5 Sample Request

```
<HTNG_DeviceCapabilityProfileRQ EchoToken="TOKEN2345" Timestamp="2001-12-17T09:30:47.0Z"
Version="1.0" Action="Add">
  <POS>
    <ota:Source>
      <ota:RequestorID Type="0" ID_Context="a" ID="12345678">
        <ota:CompanyName CompanyShortName="a"/>
      </ota:RequestorID>
    </ota:Source>
  </POS>
  <PropertyInfo ChainCode="Hotel Chain" HotelName="Hotel Name" BrandCode="Hotel BrandCode"
HotelCode="Hotel Code" HotelCodeContext="Hotel"/>
  <DeviceProfile>
    <Capabilities>
      <Capability Type="STATUS" Operation="getState">
        <OutboundParameters>
          <OutboundParameter DataType="xs:boolean" Property="State">
            <KeyValues>
              <KeyValueItem Key="On" Value="true"/>
              <KeyValueItem Key="Off" Value="false"/>
            </KeyValues>
          </OutboundParameter>
        </OutboundParameters>
      </Capability>
      <Capability Type="COMMAND" Operation="setState">
        <InboundParameters>
          <InboundParameter DataType="xs:boolean" Property="State">
            <KeyValues>
              <KeyValueItem Key="On" Value="true"/>
              <KeyValueItem Key="Off" Value="false"/>
            </KeyValues>
          </InboundParameter>
        </InboundParameters>
        <OutboundParameters>
          <OutboundParameter DataType="xs:boolean" Property="RESULT">
            <KeyValues>
              <KeyValueItem Key="SUCCESS" Value="true"/>
              <KeyValueItem Key="FAILURE" Value="false"/>
            </KeyValues>
          </OutboundParameter>
        </OutboundParameters>
      </Capability>
      <Capability Type="EVENT" Operation="stateChanged">
        <InboundParameters>
          <InboundParameter DataType="xs:boolean" Property="State">
            <KeyValues>
              <KeyValueItem Key="On" Value="true"/>
              <KeyValueItem Key="Off" Value="false"/>
            </KeyValues>
          </InboundParameter>
        </InboundParameters>
      </Capability>
    </Capabilities>
  </DeviceProfile>
</HTNG_DeviceCapabilityProfileRQ>
```

```
</HTNG_DeviceCapabilityProfileRQ>
```

3.4.6 Sample Response

```
<HTNG_DeviceCapabilityProfileRS EchoToken="TOKEN234" TimeStamp="2001-12-17T09:30:47.0Z"  
Version="1.0">  
  <Success />  
</HTNG_DeviceCapabilityProfileRS>
```

3.5 Device Discovery

3.5.1 Overview

Hotel Information Systems may need to gather device information managed by the Device Registration System.

In order to access the functionality of an Intelligent Device, the Hotel Information System must obtain properties of a device from the Device Registration System. This may include the end-point address of the device, its capabilities and physical location.


3.5.2 Roles

Role	Description	Examples
Device Discovery Requester	Any system interested in locating devices and their capabilities.	<ul style="list-style-type: none">Room Control SystemProperty Management System
Device Discovery Responder	A repository of references (for the purpose of Addressing) to servers, systems, services and devices and their capabilities.	<ul style="list-style-type: none">Registration Server

3.5.3 Use Case

Assumptions:	<ul style="list-style-type: none">The Device Discovery Responder is available.The Device Discovery Requester knows the scope of search criteria for query.
Pre-condition:	None
Trigger:	The Device Discovery Requester needs to discover devices.
Basic Course of Events:	<ol style="list-style-type: none">The Device Discovery Requester uses the Device Discovery Responder to query device information.<ol style="list-style-type: none">The query can be filtered on device properties.The Device Discovery Responder responds with the device(s) that satisfies the query.
Post-condition:	The Device Discovery Requester has the requested device information.
Exception Path:	None
Alternative Path:	None

3.5.4 Message Flows



3.5.5 Sample Request

```
<HTNG_DeviceSearchRQ EchoToken="SEARCH123" TimeStamp="2001-12-17T09:30:47.0Z" Version="1.0">
  ReturnListIndicator="false">
  <Devices>
    <!-- SEARCH BY DEVICE & PROFILE TYPE -->
    <Device Type="LOCK">
      <DeviceLocation RoomID="1024"/>
      <DeviceProfile ID="Lock"/>
    </Device>
    <!-- SEARCH BY DEVICE TYPE AND CAPABILITIES -->
    <Device Type="LAMP">
      <DeviceLocation RoomID="1024"/>
      <DeviceProfile>
        <Capabilities>
          <Capability Type="STATUS" Operation="getState"/>
        </Capabilities>
      </DeviceProfile>
    </Device>
  </Devices>
</HTNG_DeviceSearchRQ>
```

3.5.6 Sample Response

```
<HTNG_DeviceSearchRS EchoToken="TOKEN234" TimeStamp="2001-12-17T09:30:47.0Z" Version="1.0">
  <Success/>
  <Devices>
    <Device Type="Lock" ID="1129087" ModelID="String" FriendlyName="LockCo Lock" Description="IGR Lock" Class="Door Lock" ModelName="111">
      <EndpointAddress>http://htng.org/gateway/00-B0-D0-86-BB-F7</EndpointAddress>
      <DeviceProfile ID="Lock"/>
    </Device>
    <Device Type="Lamp" ID="1129087f" ModelID="String" FriendlyName="LampCo Lamp" Description="IGR Lamp" Class="Lighting" ModelName="101">
      <EndpointAddress>http://htng.org/gateway/00-B0-D0-86-BB-F7</EndpointAddress>
      <DeviceProfile>
        <Capabilities>
          <Capability Type="STATUS" Operation="getState">
            <OutboundParameters>
              <OutboundParameter DataType="xs:boolean" Property="State">
                <KeyValueItems>
                  <KeyValueItem Key="On" Value="true"/>
                  <KeyValueItem Key="Off" Value="false"/>
                </KeyValueItems>
              </OutboundParameter>
            </OutboundParameters>
          </Capability>
        </Capabilities>
      </DeviceProfile>
    </Device>
  </Devices>
</HTNG_DeviceSearchRS>
```

3.6 Interacting with Devices – Command

3.6.1 Overview

In order for applications to interact with devices in a room, devices must be able to respond to a set of supported commands issued applications.

3.6.2 Roles


Role Name	Definition	Examples
Device Control Requester	Any hotel software application or service containing feature sets based on the status of guest room devices.	<input type="checkbox"/> Guest experience management system <input type="checkbox"/> Work order management <input type="checkbox"/> Device management console <input type="checkbox"/> Property management system
Device Control Responder	A device or system (acting on behalf of another device or system) that receives commands, responds to status queries or publishes events.	<input type="checkbox"/> Device gateway <input type="checkbox"/> Zone controller <input type="checkbox"/> Set-top box <input type="checkbox"/> Intelligent light switch

3.6.3 Use Case

Assumptions:	<ul style="list-style-type: none"> • Device Control Responder has authorized the identity of the Device Control Requester. • Device Control Requester has knowledge of the capabilities of the controlled device (for example, by having previously consulted the device registry for capabilities). • Device Control Requester has allowed the Device Control Responder sufficient time to react to previously issued commands before sending additional requests.
Pre-conditions:	None
Trigger:	Device Control Requester has the need to manipulate a device.
Basic Course of Events:	<ol style="list-style-type: none"> 1) Device Control Requester submits a request. 2) Device Control Responder authenticates the request. 3) Device Control Responder executes the request. 4) Device Control Responder sends the response to the Device Control Requester.
Post-conditions:	<ul style="list-style-type: none"> • The controlled device may be in a different state. • If the Device Responder is also a Publisher, it notifies the appropriate Device Control Subscriber(s). See Interacting with Devices – Event scenario.

Exception Path:	Device is unreachable. Feature not supported.
Alternative Paths:	None

3.6.4 Message Flows



3.6.5 Sample Request – Turning on a lamp

```

<HTNG_DeviceCommandRQ EchoToken="SEARCH123" TimeStamp="2001-12-17T09:30:47.0Z"
Target="Production" Version="1.0">
  <Device Type="Lamp" ID="1129087f" Class="Lighting" />
  <Action Type="COMMAND" Operation="setState">
    <Parameters>
      <Parameter Property="State" Key="On" Value="true"/>
    </Parameters>
  </Action>
</Device>
</HTNG_DeviceCommandRQ>

```

3.6.6 Sample Response

```

<HTNG_DeviceCommandRS EchoToken="SEARCH123" TimeStamp="2001-12-17T09:30:47.0Z"
Target="Production" Version="1.0">
  <Success/>
  <Warnings>
    <Warning Code="" ShortText="" Type="" RecordID="1129087f"/>
  </Warnings>
</HTNG_DeviceCommandRS>

```

3.7 Interacting with Devices – Status

3.7.1 Overview

In order for applications to inquire about the status of devices in a room, devices must be able to respond to a set of status requests issued by an application. These are stateless operations and no values will be updated in the receiving system.

3.7.2 Roles


Role Name	Definition	Example
Device Control Requester	Any hotel software application or service containing feature sets based on the status of guest room devices.	<input type="checkbox"/> Guest experience management system <input type="checkbox"/> Work order management <input type="checkbox"/> Device management console <input type="checkbox"/> Property management system
Device Control Responder	A device or system (acting on behalf of another device or system) that receives commands, responds to status queries or publishes events.	<input type="checkbox"/> Device gateway <input type="checkbox"/> Zone controller <input type="checkbox"/> Set-top box <input type="checkbox"/> Intelligent light switch

3.7.3 Use Case

Assumptions:	<ul style="list-style-type: none"> • Device Control Responder has authorized the identity of the Device Control Requester. • Device Control Requester has knowledge of the capabilities of the controlled device (for example, by having previously consulted the device registry for capabilities). • Device Control Requester has allowed the Device Control Responder sufficient time to react to previously issued commands before sending additional requests.
Pre-conditions:	None
Trigger:	Device Control Requester has the need to check the properties of a device.
Basic Course of Events:	<ol style="list-style-type: none"> 1) Device Control Requester submits a request. 2) Device Control Responder authenticates the request. 3) Device Control Responder processes the request and returns device property values. 4) Device Control Responder sends the response to the Device Control Requester.
Post-conditions:	None

Exception Path:	Device is unreachable. Feature not supported.
Alternative Paths:	None

3.7.4 Message Flows



3.7.5 Sample Request

```

<HTNG_DeviceStatusRQ EchoToken="SEARCH123" TimeStamp="2001-12-17T09:30:47.0Z" Target="Production"
Version="1.0">
  <Devices>
    <Device Type="Lamp" ID="1129087f" Class="Lighting">
      <EndpointAddress>http://htng.org/gateway/00-B0-D0-86-BB-F7</EndpointAddress>
      <Action Type="STATUS" Operation="getState"/>
    </Device>
    <Device Type="Lamp" ID="1129087g" Class="Lighting">
      <EndpointAddress>http://htng.org/gateway/00-B0-D0-86-BB-F8</EndpointAddress>
      <Action Type="STATUS" Operation="getState"/>
    </Device>
  </Devices>
</HTNG_DeviceStatusRQ>

```

3.7.6 Sample Response

```

<HTNG_DeviceStatusRS EchoToken="SEARCH123" TimeStamp="2001-12-17T09:30:47.0Z" Target="Production"
Version="1.0">
  <Success>
  <Warnings/>
  <Devices>
    <Device Type="Lamp" ID="1129087f" Class="Lighting">
      <EndpointAddress>http://htng.org/gateway/00-B0-D0-86-BB-F7</EndpointAddress>
      <Action Type="STATUS" Operation="getState">
        <Parameters>
          <Parameter Property="State" Key="On" Value="true"/>
        </Parameters>
      </Action>
    </Device>
    <Device Type="Lamp" ID="1129087g" Class="Lighting">
      <EndpointAddress>http://htng.org/gateway/00-B0-D0-86-BB-F8</EndpointAddress>
      <Action Type="STATUS" Operation="getState">
        <Parameters>
          <Parameter Property="State" Key="Off" Value="false"/>
        </Parameters>
      </Action>
    </Device>
  </Devices>
</HTNG_DeviceStatusRS>

```

3.8 Interacting with Devices – Event

3.8.1 Overview

As the status of a device changes, it may notify other systems or devices about these changes by issuing events.


3.8.2 Roles

Role Name	Definition	Example
Device Control Subscriber	Any hotel software application or service interested in being notified of changes to properties occurring in a guest room device.	<input type="checkbox"/> Guest experience management system <input type="checkbox"/> Work order management <input type="checkbox"/> Device management console <input type="checkbox"/> Property management system
Device Control Publisher	Any device or system capable of monitoring and publishing device property changes.	<input type="checkbox"/> Device gateway <input type="checkbox"/> Zone controller <input type="checkbox"/> Set-top box <input type="checkbox"/> Intelligent light switch

3.8.3 Use Case

Assumptions:	<ul style="list-style-type: none"> • Device Control Subscriber can authorize the identity of the Device Control Publisher. • Device Control Subscriber is fully functional and accessible.
Pre-condition:	At least one Device Control Subscriber has successfully registered interest in receiving events raised by the Device Control Publisher.
Trigger:	A device property value has changed.
Basic Course of Events:	<ol style="list-style-type: none"> 1) Device Control Publisher enumerates all Device Control Subscribers that have registered. 2) Device Control Publisher creates appropriate message payload. 3) Device Control Publisher submits the message payload to the Device Control Subscriber(s).
Post-conditions:	None
Exception Path:	Subscriber is unreachable. Feature not supported.
Alternative Paths:	None

3.8.4 Message Flows



3.8.5 Sample Request

```
<HTNG_DeviceEventRQ EchoToken="SEARCH123" Timestamp="2001-12-17T09:30:47.0Z" Target="Production"
Version="1.0">
  <Device Type="Lamp" ID="1129087f" Class="Lighting">
    <EndpointAddress>http://htng.org/gateway/00-B0-D0-86-BB-F7</EndpointAddress>
    <Action Type="EVENT" Operation="StateChanged">
      <Parameters>
        <Parameter Property="State" Key="On" Value="true" PreviousValue="false"/>
      </Parameters>
    </Action>
  </Device>
</HTNG_DeviceEventRQ>
```

3.8.6 Sample Response

```
<HTNG_DeviceEventRS EchoToken="SEARCH123" Timestamp="2001-12-17T09:30:47.0Z" Target="Production"
Version="1.0">
  <Success/>
</HTNG_DeviceEventRS>
```

4 Messages

4.1 Guest Room Status Check

4.1.1 Data Element Table – Request

Element @Attribute	Num	Description/Contents
HTNG_HotelRoomStatusSearchRQ	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_HotelRoomStatusSearchRQ / POS / Source	1	This holds details regarding the requestor. It may be repeated to also accommodate the delivery systems.
HTNG_HotelRoomStatusSearchRQ / POS / Source / RequestorID	1	An identifier of the entity making the request (e.g., ATA/IATA/ID number, Electronic Reservation Service Provider (ERSP), Association of British Travel Agents (ABTA)).
@Type	0..1	A reference to the type of object defined by the UniqueID element. Refer to OpenTravel Code List Unique ID Type (UIT).
@ID_Context	0..1	Used to identify the source of the identifier (e.g., IATA, ABTA).
@ID	1	A unique identifying value assigned by the creating system. The ID attribute may be used to reference a primary-key value within a database or in a particular implementation.
HTNG_HotelRoomStatusSearchRQ / PropertyInfo	1	Identifies a specific hotel by using the Chain Code, the Brand Code, and the Hotel Code. The codes used are agreed upon by trading partners.

Element @Attribute	Num	Description/Contents
@HotelCode	1	The code that uniquely identifies a single hotel property. The hotel code is decided between vendors.
@BrandCode	0..1	A code that identifies the brand or flag of a hotel, often used for independently-owned or franchised properties who are known by a specific brand.
@ChainCode	0..1	The code that identifies a hotel chain or management group. The hotel chain code is decided between vendors. This attribute is optional if the hotel is an independent property that can be identified by the HotelCode attribute.
HTNG_HotelRoomStatusSearchR Q / Room	1	Used to convey information about a single room or a suite comprised of room components. The populated values on this entity are used as the query parameters.
@RoomID	0..1	The room number.
HTNG_HotelRoomStatusSearchR Q / Room / RoomType	0..1	A container element which holds information describing the room.
@Building	0..1	The building in which the room is located.
@Floor	0..1	The floor on which the room is located.
@Wing	0..1	The wing on which the room is located.
@RoomLocationCode	0..1	Indicates the location of the room within the hotel structure. Typical values would be "Near Exit", "Close to elevator", "Low Floor" or "High Floor". Refer to OpenTravel Code List Room Location Type (RLT).
HTNG_HotelRoomStatusSearchR Q / Room / Devices	0..1	A collection of Devices.
HTNG_HotelRoomStatusSearchR Q / Room / Devices / Device	1..n	Container element which holds information describing the device.
@ID	0..1	An identifier that is unique within the network.
@FriendlyName	0..1	A name used to identify a device in a room.
@Class	0..1	General classification of the device, ie HVAC, TelevisionIntegration, etc.

Element @Attribute	Num	Description/Contents
@Type	0..1	Specific classification of the device, ie Thermostat, SetTopBox, etc.
@Description	0..1	Text Description of the device.
HTNG_HotelRoomStatusSearchR Q / Room / TelephoneExtensions	0..1	A collection of telephone extensions.
HTNG_HotelRoomStatusSearchR Q / Room / TelephoneExtensions / TelephoneExtension	1..n	A telephone extension that is part of a single room or a suite of component rooms.

4.1.2 Data Element Table – Response

Element @Attribute	Num	Description/Contents
HTNG_HotelRoomStatusSearchR S	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_HotelRoomStatusSearchR S / Success	0..1	The presence of the empty Success element explicitly indicates that the OpenTravel versioned message succeeded.
HTNG_HotelRoomStatusSearchR S / Warnings	0..1	Used in conjunction with the Success element to define one or more business errors.
HTNG_HotelRoomStatusSearchR S / Warnings / Warning	1..n	Used when a message has been successfully processed to report any warnings or business errors that occurred.

Element @Attribute	Num	Description/Contents
@Type	1	The Warning element MUST contain the Type attribute that uses a recommended set of values to indicate the warning type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_HotelRoomStatusSearchR Q / Errors	0..1	A collection of errors that occurred during the processing of a message.
HTNG_HotelRoomStatusSearchR Q / Errors / Error	1..n	An error that occurred during the processing of a message.
@Type	1	The Error element MUST contain the Type attribute that uses a recommended set of values to indicate the error type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.

Element @Attribute	Num	Description/Contents
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_HotelRoomStatusSearchR S / RoomInformationList	0..1	The result set generated by the query sent in the request.
HTNG_HotelRoomStatusSearchR S / RoomInformationList / RoomInformation	1..n	A container element used to hold room and reservation information.
HTNG_HotelRoomStatusSearchR S / RoomInformationList / RoomInformation / Room	1	Used to convey information about a single room or a suite comprised of room components.
@RoomID	1	The room number.
HTNG_HotelRoomStatusSearchR S / RoomInformationList / RoomInformation / Room / Devices	0..1	A collection of Devices.
HTNG_HotelRoomStatusSearchR S / RoomInformationList / RoomInformation / Room / Devices / Device	1..n	Container element which holds information describing the device.
@ID	1	An identifier that is unique within the network.
@FriendlyName	0..1	A name used to identify a device in a room.
@Class	1	General classification of the device, i.e. HVAC, TelevisionIntegration, etc.
@Type	0..1	Specific classification of the device, i.e. Thermostat, SetTopBox, etc.
@Description	1	Text Description of the device.
HTNG_HotelRoomStatusSearchR S / RoomInformationList / RoomInformation / Room / Devices / Device / CurrentHealthStatus	1	Container element that contains the current operational status of the device.

Element @Attribute	Num	Description/Contents
@Value	1	The enumerated operational status of the device.
@Reason	0..1	Text description of the reason for the device operational status.

4.2 Guest Room Status Event Notification

4.2.1 Data Element Table – Request

Element @Attribute	Num	Description/Contents
HTNG_HotelRoomStatusUpdateNotificationRQ	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_HotelRoomStatusUpdateNotificationRQ / POS / Source	1	This holds details regarding the requestor. It may be repeated to also accommodate the delivery systems.
HTNG_HotelRoomStatusUpdateNotificationRQ / POS / Source / RequestorID	1	An identifier of the entity making the request (e.g., ATA/IATA/ID number, Electronic Reservation Service Provider (ERSP), Association of British Travel Agents (ABTA)).
@Type	0..1	A reference to the type of object defined by the UniqueID element. Refer to OpenTravel Code List Unique ID Type (UIT).
@ID_Context	0..1	Used to identify the source of the identifier (e.g., IATA, ABTA).
@ID	1	A unique identifying value assigned by the creating system. The ID attribute may be used to reference a primary-key value within a database or in a particular implementation.

Element @Attribute	Num	Description/Contents
HotelRoomStatusUpdateNotifRQ / PropertyInfo	1	Identifies a specific hotel by using the Chain Code, the Brand Code, and the Hotel Code. The codes used are agreed upon by trading partners.
@HotelCode	1	The code that uniquely identifies a single hotel property. The hotel code is decided between vendors.
@BrandCode	0..1	A code that identifies the brand or flag of a hotel, often used for independently-owned or franchised properties who are known by a specific brand.
@ChainCode	0..1	The code that identifies a hotel chain or management group. The hotel chain code is decided between vendors. This attribute is optional if the hotel is an independent property that can be identified by the HotelCode attribute.
HotelRoomStatusUpdateNotifRQ / Room	1	Used to convey information about a single room or a suite comprised of room components.
@RoomID	1	The room number.
HotelRoomStatusUpdateNotifRQ / Room / Devices	1	A collection of Devices.
HotelRoomStatusUpdateNotifRQ / Room / Devices / Device	1..n	Container element which holds information describing the device.
@ID	0..1	An identifier that is unique within the network.
@FriendlyName	0..1	A name used to identify a device in a room.
@Description	1	Text Description of the device.
@Class	1	General classification of the device, ie HVAC, TelevisionIntegration, etc.
@Type	0..1	Specific classification of the device, ie Thermostat, SetTopBox, etc.
HotelRoomStatusUpdateNotifRQ / Room / Devices / Device / PriorHealthStatus	0..1	Container element that contains the previous operational status for the device.
@Value	1	The enumerated operational status of the device.
@Reason	0..1	Text description of the reason for the device operational status.

Element @Attribute	Num	Description/Contents
HotelRoomStatusUpdateNotifRQ / Room / Devices / Device / CurrentHealthStatus	1	Container element that contains the current operational status of the device.
@Value	1	The enumerated operational status of the device.
@Reason	0..1	Text description of the reason for the device operational status.

4.2.2 Data Element Table – Response

Element @Attribute	Num	Description/Contents
HTNG_HotelRoomStatusUpdateNotifRS	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_HotelRoomStatusUpdateNotifRS / Success	0..1	The presence of the empty Success element explicitly indicates that the OpenTravel versioned message succeeded.
HTNG_HotelRoomStatusUpdateNotifRS / Warnings	0..1	Used in conjunction with the Success element to define one or more business errors.
HTNG_HotelRoomStatusUpdateNotifRS / Warnings / Warning	1..n	Used when a message has been successfully processed to report any warnings or business errors that occurred.

Element @Attribute	Num	Description/Contents
@Type	1	The Warning element MUST contain the Type attribute that uses a recommended set of values to indicate the warning type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_HotelRoomStatusUpdate NotifRS / Errors	0..1	A collection of errors that occurred during the processing of a message.
HTNG_HotelRoomStatusUpdate NotifRS / Errors / Error	1..n	An error that occurred during the processing of a message.
@Type	1	The Error element MUST contain the Type attribute that uses a recommended set of values to indicate the error type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.

Element @Attribute	Num	Description/Contents
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).

4.3 Device Registration

4.3.1 Data Element Table – Request

Element @Attribute	Num	Description/Contents
HTNG_DeviceRegistrationRQ	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceRegistrationRQ / POS	1	POS provides a mechanism to indicate the source of the message.
HTNG_DeviceRegistrationRQ / POS / Source	1	This holds details regarding the requestor. It may be repeated to also accommodate the delivery systems.
HTNG_DeviceRegistrationRQ / POS / Source / RequestorID	1	An identifier of the entity making the request (e.g., ATA/IATA/ID number, Electronic Reservation Service Provider (ERSP), Association of British Travel Agents (ABTA)).
@Type	0..1	A reference to the type of object defined by the UniqueID element. Refer to OpenTravel Code List Unique ID Type (UIT).

Element @Attribute	Num	Description/Contents
@ID	1	A unique identifying value assigned by the creating system. The ID attribute may be used to reference a primary-key value within a database or in a particular implementation.
@ID_Context	0..1	Used to identify the source of the identifier (e.g., IATA, ABTA).
HTNG_DeviceRegistrationRQ / POS / Source / RequestorID / CompanyName	0..1	Identifies the company that is associated with the UniqueID.
@CompanyShortName	1	Used to provide the company common name.
HTNG_DeviceRegistrationRQ / PropertyInfo	1	Identifies a specific hotel by using the Chain Code, the Brand Code, and the Hotel Code. The codes used are agreed upon by trading partners.
@HotelCode	1	The code that uniquely identifies a single hotel property. The hotel code is decided between vendors.
@ChainCode	0..1	The code that identifies a hotel chain or management group. The hotel chain code is decided between vendors. This attribute is optional if the hotel is an independent property that can be identified by the HotelCode attribute.
@BrandCode	0..1	A code that identifies the brand or flag of a hotel, often used for independently-owned or franchised properties who are known by a specific brand.
@HotelCodeContext	0..1	A text field used to communicate the context (or source of - ex Sabre, Galileo, Worldspan, Amadeus) the HotelReferenceGroup codes.
HTNG_DeviceRegistrationRQ / Devices	1	A collection of Devices.
HTNG_DeviceRegistrationRQ / Devices / Device	1..n	Container element which holds information describing the device.
@Type	1	Specific classification of the device, ie Thermostat, SetTopBox, etc.
@ID	1	An identifier that is unique within the network.
@ModelID	0..1	The model of the device as provided by the manufacturer.

Element @Attribute	Num	Description/Contents
@SerialNumber	0..1	The serial number of the device as provided by the manufacturer.
@MAC_Address	0..1	A unique identifier assigned to network devices.
@FriendlyName	1	A name used to identify a device in a room.
@Description	0..1	Text Description of the device.
@Class	1	General classification of the device, ie HVAC, TelevisionIntegration, etc.
@ModelName	0..1	The model of the device as provided by the manufacturer.
HTNG_DeviceRegistrationRQ / Devices / Device / EndpointAddress	1	Unique endpoint address of this device.
HTNG_DeviceRegistrationRQ / Devices / Device / Manufacturer	0..1	A container element containing information about the manufacturer of the device.
@Type	1	A reference to the type of object defined by the UniqueID element. Refer to OpenTravel Code List Unique ID Type (UIT).
@ID	1	A unique identifier assigned to a given manufacturer.
@ID_Context	0..1	Used to identify the source of the identifier (e.g., IATA, ABTA).
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceLocation	1	A container element containing information about where a device is located.
@RoomID	0..1*	Room Number where this particular device is located. (*Either RoomID of TelephoneExtensions MUST be used.)
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceLocation / RoomType	0..1	A container element used to describe certain facets of where a device is located.
@Building	0..1	The building in which the room is located.
@Floor	0..1	The floor on which the room is located.
@Wing	0..1	The wing on which the room is located.

Element @Attribute	Num	Description/Contents
@RoomLocationCode	0..1	Indicates the location of the room within the hotel structure. Typical values would be "Near Exit", "Close to elevator", "Low Floor" or "High Floor". Refer to OpenTravel Code List Room Location Type (RLT).
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceLocation / TelephoneExtensions	0..1*	A collection of telephone extensions. (*Either RoomID of TelephoneExtensions MUST be used.)
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceLocation / TelephoneExtensions / TelephoneExtension	1..n	A telephone extension that is part of a single room or a suite of component rooms.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile	1	An element used to describe the set of available capabilities.
@ID	0..1*	A reference to an established Device Profile (See Device Capability Profile Management use case). If this value is populated, do not include the Capabilities collection.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile / Capabilities	0..1*	A collection of Capability elements used to convey device behaviors and interactions. This collection should only be present if not using Device Capability Profiles.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile Capabilities / Capability	1..n	An individual behavior.
@Type	1	One of 4 values (Per the DMS specification): <ul style="list-style-type: none"> • STATUS - Obtains the status of a given property of a device. • COMMAND - Instruction to the device to perform an action. • EVENT - Callback to indicate a device property has changed. • VENDOR_SPECIFIC - Vendor specific implementation.
@Operation	1	The method/function that can/will called.

Element @Attribute	Num	Description/Contents
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile Capabilities / Capability / OutboundParameters	0..1	A collection of elements used to convey the parameters passed to the function call.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile Capabilities / Capability / OutboundParameters / OutboundParameter	1..n	A single parameter.
@DataType	1	The XML schema data type of the parameter.
@Property	1	The name of the property.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile Capabilities / Capability / OutboundParameters / OutboundProperty / KeyValueltems	0..1	A collection of enumerable items used to constrain the allowable values for the type referenced by the @Property.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile Capabilities / Capability / OutboundParameters / OutboundProperty / KeyValueltems / KeyValueltem	1..n	An individual item in the enumeration.
@Key	1	The abstract display name corresponding to the Value.
@Value	1	Corresponds to the value of the OutboundParameter@DataType.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile Capabilities / Capability / InboundParameters	0..1	A collection of elements used to convey the parameters returned by the function call.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile Capabilities / Capability / InboundParameters / InboundParameter	1..n	A single parameter.

Element @Attribute	Num	Description/Contents
@DataType	1	The XML schema data type of the parameter.
@Property	1	The name of the property.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile Capabilities / Capability / InboundParameters / InboundProperty / KeyValuelItems	0..1	A collection of enumerable items used to constrain the allowable values for the type referenced by the @Property.
HTNG_DeviceRegistrationRQ / Devices / Device / DeviceProfile Capabilities / Capability / InboundParameters / InboundProperty / KeyValuelItems / KeyValuelItem	1..n	An individual item in the enumeration.
@Key	1	The abstract display name corresponding to the Value.
@Value	1	Corresponds to the value of the OutboundParameter@DataType.
HTNG_DeviceRegistrationRQ / TPA_Extensions	0..1	This is used to exchange custom/implementation-specific values that are agreed upon between trading partners.

4.3.2 Data Element Table – Response

Element @Attribute	Num	Description/Contents
HTNG_DeviceRegistrationRS	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).

Element @Attribute	Num	Description/Contents
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceRegistrationRS / Success	0..1	The presence of the empty Success element explicitly indicates that the OpenTravel versioned message succeeded.
HTNG_DeviceRegistrationRS / Warnings	0..1	Used in conjunction with the Success element to define one or more business errors.
HTNG_DeviceRegistrationRS / Warnings / Warning	1..n	Used when a message has been successfully processed to report any warnings or business errors that occurred.
@Type	1	The Warning element MUST contain the Type attribute that uses a recommended set of values to indicate the warning type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type = "Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_DeviceRegistrationRS / Errors	0..1	A collection of errors that occurred during the processing of a message.
HTNG_DeviceRegistrationRS / Errors / Error	1..n	An error that occurred during the processing of a message.

Element @Attribute	Num	Description/Contents
@Type	1	The Error element MUST contain the Type attribute that uses a recommended set of values to indicate the error type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type = "Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).

4.4 Device Capability Profile Management

4.4.1 Data Element Table – Request

Element @Attribute	Num	Description/Contents
HTNG_DeviceCapabilityProfileRQ	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.

Element @Attribute	Num	Description/Contents
HTNG_DeviceCapabilityProfileRQ / POS	1	POS provides a mechanism to indicate the source of the message.
HTNG_DeviceCapabilityProfileRQ / POS / Source	1	This holds details regarding the requestor. It may be repeated to also accommodate the delivery systems.
HTNG_DeviceCapabilityProfileRQ / POS / Source / RequestorID	1	An identifier of the entity making the request (e.g., ATA/IATA/ID number, Electronic Reservation Service Provider (ERSP), Association of British Travel Agents (ABTA)).
@Type	0..1	A reference to the type of object defined by the UniqueID element. Refer to OpenTravel Code List Unique ID Type (UIT).
@ID	1	A unique identifying value assigned by the creating system. The ID attribute may be used to reference a primary-key value within a database or in a particular implementation.
@ID_Context	0..1	Used to identify the source of the identifier (e.g., IATA, ABTA).
HTNG_DeviceCapabilityProfileRQ / POS / Source / RequestorID / CompanyName	0..1	Identifies the company that is associated with the UniqueID.
@CompanyShortName	1	Used to provide the company common name.
HTNG_DeviceCapabilityProfileRQ / PropertyInfo	1	Identifies a specific hotel by using the Chain Code, the Brand Code, and the Hotel Code. The codes used are agreed upon by trading partners.
@HotelCode	1	The code that uniquely identifies a single hotel property. The hotel code is decided between vendors.
@ChainCode	0..1	A code that identifies the brand or flag of a hotel, often used for independently-owned or franchised properties who are known by a specific brand.
@BrandCode	0..1	The code that identifies a hotel chain or management group. The hotel chain code is decided between vendors. This attribute is optional if the hotel is an independent property that can be identified by the HotelCode attribute.

Element @Attribute	Num	Description/Contents
@HotelCodeContext	0..1	A text field used to communicate the context (or source of – ex Sabre, Galileo, Worldspan, Amadeus) the HotelReferenceGroup codes.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile	1	An element used to describe the set of available capabilities.
@ID	0..1*	A reference to an established Device Profile (See Device Capability Profile Management use case). If this value is populated, do not include the Capabilities collection.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities	0..1*	A collection of Capability elements used to convey device behaviors and interactions. This collection should only be present if not using Device Capability Profiles.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities / Capability	1..n	An individual behavior.
@Type	1	One of 4 values (Per the DMS specification): <ul style="list-style-type: none"> • STATUS – Obtains the status of a given property of a device. • COMMAND – Instruction to the device to perform an action. • EVENT – Callback to indicate a device property has changed. • VENDOR_SPECIFIC – Vendor specific implementation.
@Operation	1	The method/function that can/will called.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities / Capability / OutboundParameters	0..1	A collection of elements used to convey the parameters passed to the function call.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities / Capability / OutboundParameters / OutboundParameter	1..n	A single parameter.
@DataType	1	The XML schema data type of the parameter.
@Property	1	The name of the property.

Element @Attribute	Num	Description/Contents
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities / Capability / OutboundParameters / OutboundProperty / KeyValueltems	0..1	A collection of enumerable items used to constrain the allowable values for the type referenced by the @Property.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities / Capability / OutboundParameters / OutboundProperty / KeyValueltems / KeyValueltem	1..n	An individual item in the enumeration.
@Key	1	The abstract display name corresponding to the Value.
@Value	1	Corresponds to the value of the OutboundParameter@DataType.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities / Capability / InboundParameters	0..1	A collection of elements used to convey the parameters returned by the function call.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities / Capability / InboundParameters / InboundParameter	1..n	A single parameter.
@DataType	1	The XML schema data type of the parameter.
@Property	1	The name of the property.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities / Capability / InboundParameters / InboundProperty / KeyValueltems	0..1	A collection of enumerable items used to constrain the allowable values for the type referenced by the @Property.
HTNG_DeviceCapabilityProfileRQ / DeviceProfile / Capabilities / Capability / InboundParameters / InboundProperty / KeyValueltems / KeyValueltem	1..n	An individual item in the enumeration.
@Key	1	The abstract display name corresponding to the Value.

Element @Attribute	Num	Description/Contents
@Value	1	Corresponds to the value of the OutboundParameter@DataType.
HTNG_DeviceCapabilityProfileRQ / TPA_Extensions	0..1	This is used to exchange custom/implementation-specific values that are agreed upon between trading partners.

4.4.2 Data Element Table – Response

Element @Attribute	Num	Description/Contents
HTNG_DeviceCapabilityProfileRS	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceCapabilityProfileRS / Success	0..1	The presence of the empty Success element explicitly indicates that the OpenTravel versioned message succeeded.
HTNG_DeviceCapabilityProfileRS / Warnings	0..1	Used in conjunction with the Success element to define one or more business errors.
HTNG_DeviceCapabilityProfileRS / Warnings / Warning	1..n	Used when a message has been successfully processed to report any warnings or business errors that occurred.
@Type	1	The Warning element MUST contain the Type attribute that uses a recommended set of values to indicate the warning type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type = "Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).

Element @Attribute	Num	Description/Contents
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_DeviceCapabilityProfileRS / Errors	0..1	A collection of errors that occurred during the processing of a message.
HTNG_DeviceCapabilityProfileRS / Errors / Error	1..n	An error that occurred during the processing of a message.
@Type	1	The Error element MUST contain the Type attribute that uses a recommended set of values to indicate the error type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).

4.5 Device Endpoint Discovery

4.5.1 Data Element Table – Request

Element @Attribute	Num	Description/Contents
HTNG_DeviceSearchRQ	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceSearchRQ / POS	1	POS provides a mechanism to indicate the source of the message.
HTNG_DeviceSearchRQ / POS / Source	1	This holds details regarding the requestor. It may be repeated to also accommodate the delivery systems.
HTNG_DeviceSearchRQ / POS / Source / RequestorID	1	An identifier of the entity making the request (e.g., ATA/IATA/ID number, Electronic Reservation Service Provider (ERSP), Association of British Travel Agents (ABTA)).
@Type	0..1	A reference to the type of object defined by the UniqueID element. Refer to OpenTravel Code List Unique ID Type (UIT).
@ID	1	A unique identifying value assigned by the creating system. The ID attribute may be used to reference a primary-key value within a database or in a particular implementation.
@ID_Context	0..1	Used to identify the source of the identifier (e.g., IATA, ABTA).
HTNG_DeviceSearchRQ / POS / Source / RequestorID / CompanyName	0..1	Identifies the company that is associated with the UniqueID.
@CompanyShortName	1	Used to provide the company common name.

Element @Attribute	Num	Description/Contents
HTNG_DeviceSearchRQ / PropertyInfo	1	Identifies a specific hotel by using the Chain Code, the Brand Code, and the Hotel Code. The codes used are agreed upon by trading partners.
@HotelCode	1	The code that uniquely identifies a single hotel property. The hotel code is decided between vendors.
@ChainCode	0..1	A code that identifies the brand or flag of a hotel, often used for independently-owned or franchised properties who are known by a specific brand.
@BrandCode	0..1	The code that identifies a hotel chain or management group. The hotel chain code is decided between vendors. This attribute is optional if the hotel is an independent property that can be identified by the HotelCode attribute.
@HotelCodeContext	0..1	A text field used to communicate the context (or source of – ex Sabre, Galileo, Worldspan, Amadeus) the HotelReferenceGroup codes.
HTNG_DeviceSearchRQ / Devices	1	A collection of Devices.
HTNG_DeviceSearchRQ / Devices / Device	0..n	Container element which holds information describing the device.
@Type	0..1	Specific classification of the device, ie Thermostat, SetTopBox, etc.
HTNG_DeviceSearchRQ / Devices / Device / DeviceLocation	0..1	
@RoomID	1	Room Number where this particular device is located.
HTNG_DeviceSearchRQ / Devices / Device / DeviceProfile	1	An element used to describe the set of available capabilities.
@ID	0..1*	A reference to an established Device Profile (See Device Capability Profile Management use case). If this value is populated, do not include the Capabilities collection.
HTNG_DeviceSearchRQ / Devices / Device / DeviceProfile Capabilities	0..1*	A collection of Capability elements used to convey device behaviors and interactions. This collection should only be present if not using Device Capability Profiles.

Element @Attribute	Num	Description/Contents
HTNG_DeviceSearchRQ / Devices / Device / DeviceProfile Capabilities / Capability	1..n	An individual behavior.
@Type	1	One of 4 values (Per the DMS specification): <ul style="list-style-type: none"> • STATUS - Obtains the status of a given property of a device. • COMMAND - Instruction to the device to perform an action. • EVENT - Callback to indicate a device property has changed. • VENDOR_SPECIFIC - Vendor specific implementation.
@Operation	1	The method/function that can/will called.

4.5.2 Data Element Table – Response

Element @Attribute	Num	Description/Contents
HTNG_DeviceSearchRS	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceSearchRS / Success	0..1	The presence of the empty Success element explicitly indicates that the OpenTravel versioned message succeeded.
HTNG_DeviceSearchRS / Warnings	0..1	Used in conjunction with the Success element to define one or more business errors.

Element @Attribute	Num	Description/Contents
HTNG_DeviceSearchRS / Warnings / Warning	1..n	Used when a message has been successfully processed to report any warnings or business errors that occurred.
@Type	1	The Warning element MUST contain the Type attribute that uses a recommended set of values to indicate the warning type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type = "Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_DeviceSearchRS / Errors	0..1	A collection of errors that occurred during the processing of a message.
HTNG_DeviceSearchRS / Errors / Error	1..n	An error that occurred during the processing of a message.
@Type	1	The Error element MUST contain the Type attribute that uses a recommended set of values to indicate the error type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type = "Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).

Element @Attribute	Num	Description/Contents
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_DeviceSearchRS / Devices	1	A collection of Devices.
HTNG_DeviceSearchRS / Devices / Device	1..n	Container element which holds information describing the device.
@Type	1	Specific classification of the device, ie Thermostat, SetTopBox, etc.
@ID	1	An identifier that is unique within the network.
@ModelID	0..1	The model of the device as provided by the manufacturer.
@SerialNumber	0..1	The serial number of the device as provided by the manufacturer.
@MAC_Address	0..1	A unique identifier assigned to network devices.
@FriendlyName	1	A name used to identify a device in a room.
@Description	0..1	Text Description of the device.
@Class	1	General classification of the device, ie HVAC, TelevisionIntegration, etc.
@ModelName	0..1	The model of the device as provided by the manufacturer.
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile	0..1	An element used to describe the set of available capabilities.
@ID	0..1*	A reference to an established Device Profile (See Device Capability Profile Management use case). If this value is populated, do not include the Capabilities collection.

Element @Attribute	Num	Description/Contents
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities	0..1*	A collection of Capability elements used to convey device behaviors and interactions. This collection should only be present if not using Device Capability Profiles.
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities / Capability	1..n	An individual behavior.
@Type	1	One of 4 values (Per the DMS specification): <ul style="list-style-type: none"> • STATUS - Obtains the status of a given property of a device. • COMMAND - Instruction to the device to perform an action. • EVENT - Callback to indicate a device property has changed. • VENDOR_SPECIFIC - Vendor specific implementation.
@Operation	1	The method/function that can/will called.
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities / Capability / OutboundParameters	0..1	A collection of elements used to convey the parameters passed to the function call.
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities / Capability / OutboundParameters / OutboundParameter	1..n	A single parameter.
@DataType	1	The XML schema data type of the parameter.
@Property	1	The name of the property.
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities / Capability / OutboundParameters / OutboundParameter / KeyValueltems	0..1	A collection of enumerable items used to constrain the allowable values for the type referenced by the @Property.

Element @Attribute	Num	Description/Contents
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities / Capability / OutboundParameters / OutboundParameter / KeyValueltems / KeyValueltem	1..n	An individual item in the enumeration.
@Key	1	The abstract display name corresponding to the Value.
@Value	1	Corresponds to the value of the OutboundParameter@DataType.
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities / Capability / InboundParameters	0..1	A collection of elements used to convey the parameters returned by the function call.
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities / Capability / InboundParameters / InboundParameter	1..n	A single parameter.
@DataType	1	The XML schema data type of the parameter.
@Property	1	The name of the property.
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities / Capability / InboundParameters / InboundParameter / KeyValueltems	0..1	A collection of enumerable items used to constrain the allowable values for the type referenced by the @Property.
HTNG_DeviceSearchRS / Devices / Device / DeviceProfile Capabilities / Capability / InboundParameters / InboundParameter / KeyValueltems / KeyValueltem	1..n	An individual item in the enumeration.
@Key	1	The abstract display name corresponding to the Value.
@Value	1	Corresponds to the value of the OutboundParameter@DataType.

Element @Attribute	Num	Description/Contents
HTNG_DeviceSearchRS / TPA_Extensions	0..1	This is used to exchange custom/implementation-specific values that are agreed upon between trading partners.

4.6 Interacting with Devices - Command

4.6.1 Data Element Table – Request

Element @Attribute	Num	Description/Contents
HTNG_DeviceCommandRQ	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceCommandRQ / POS	1	POS provides a mechanism to indicate the source of the message.
HTNG_DeviceCommandRQ / POS / Source	1	This holds details regarding the requestor. It may be repeated to also accommodate the delivery systems.
HTNG_DeviceCommandRQ / POS / Source / RequestorID	1	An identifier of the entity making the request (e.g., ATA/IATA/ID number, Electronic Reservation Service Provider (ERSP), Association of British Travel Agents (ABTA)).
@Type	0..1	A reference to the type of object defined by the UniqueID element. Refer to OpenTravel Code List Unique ID Type (UIT).
@ID	1	A unique identifying value assigned by the creating system. The ID attribute may be used to reference a primary-key value within a database or in a particular implementation.

Element @Attribute	Num	Description/Contents
@ID_Context	0..1	Used to identify the source of the identifier (e.g., IATA, ABTA).
HTNG_DeviceCommandRQ / POS / Source / RequestorID / CompanyName	0..1	Identifies the company that is associated with the UniqueID.
@CompanyShortName	1	Used to provide the company common name.
HTNG_DeviceCommandRQ / PropertyInfo	1	Identifies a specific hotel by using the Chain Code, the Brand Code, and the Hotel Code. The codes used are agreed upon by trading partners.
@HotelCode	1	The code that uniquely identifies a single hotel property. The hotel code is decided between vendors.
@ChainCode	0..1	A code that identifies the brand or flag of a hotel, often used for independently-owned or franchised properties who are known by a specific brand.
@BrandCode	0..1	The code that identifies a hotel chain or management group. The hotel chain code is decided between vendors. This attribute is optional if the hotel is an independent property that can be identified by the HotelCode attribute.
@HotelCodeContext	0..1	A text field used to communicate the context (or source of – ex Sabre, Galileo, Worldspan, Amadeus) the HotelReferenceGroup codes.
HTNG_DeviceCommandRQ / Device	1	Container element which holds information describing the device.
@Type	0..1	Specific classification of the device, i.e. Thermostat, SetTopBox, etc.
@ID	1	An identifier that is unique within the network.
@Class	0..1	General classification of the device, ie HVAC, TelevisionIntegration, etc.
HTNG_DeviceCommandRQ / Device / EndPointAddress	1	Unique endpoint address of this device.
HTNG_DeviceCommandRQ / Device / Action	1	A container element that wraps a given command.
@Type	1	Must be equal to “COMMAND”
@Operation	1	The method/function that is being called.

Element @Attribute	Num	Description/Contents
HTNG_DeviceCommandRQ / Device / Action / Parameters	0..1	A collection of elements used to convey the parameters passed to the function call.
HTNG_DeviceCommandRQ / Device / Action / Parameters / Parameter	1..n	A single parameter.
@Property	1	The name of the property
@Key	0..1	The abstract display name corresponding to the Value.
@Value	1	The value of the Property

4.6.2 Data Element Table – Response

Element @Attribute	Num	Description/Contents
HTNG_DeviceCommandRS	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceCommandRS / Success	0..1	The presence of the empty Success element explicitly indicates that the OpenTravel versioned message succeeded.
HTNG_DeviceCommandRS / Warnings	0..1	Used in conjunction with the Success element to define one or more business errors.
HTNG_DeviceCommandRS / Warnings / Warning	1..n	Used when a message has been successfully processed to report any warnings or business errors that occurred.

Element @Attribute	Num	Description/Contents
@Type	1	The Warning element MUST contain the Type attribute that uses a recommended set of values to indicate the warning type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_DeviceCommandRS / Errors	0..1	A collection of errors that occurred during the processing of a message.
HTNG_DeviceCommandRS / Errors / Error	1..n	An error that occurred during the processing of a message.
@Type	1	The Error element MUST contain the Type attribute that uses a recommended set of values to indicate the error type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.

Element @Attribute	Num	Description/Contents
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).

4.7 Interacting with Devices - Status

4.7.1 Data Element Table – Request

Element @Attribute	Num	Description/Contents
HTNG_DeviceStatusRQ	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceStatusRQ / POS	1	POS provides a mechanism to indicate the source of the message.
HTNG_DeviceStatusRQ / POS / Source	1	This holds details regarding the requestor. It may be repeated to also accommodate the delivery systems.
HTNG_DeviceStatusRQ / POS / Source / RequestorID	1	An identifier of the entity making the request (e.g., ATA/IATA/ID number, Electronic Reservation Service Provider (ERSP), Association of British Travel Agents (ABTA)).
@Type	0..1	A reference to the type of object defined by the UniqueID element. Refer to OpenTravel Code List Unique ID Type (UIT).

Element @Attribute	Num	Description/Contents
@ID	1	A unique identifying value assigned by the creating system. The ID attribute may be used to reference a primary-key value within a database or in a particular implementation.
@ID_Context	0..1	Used to identify the source of the identifier (e.g., IATA, ABTA).
HTNG_DeviceStatusRQ / POS / Source / RequestorID / CompanyName	0..1	Identifies the company that is associated with the UniqueID.
@CompanyShortName	1	Used to provide the company common name.
HTNG_DeviceStatusRQ / PropertyInfo	1	Identifies a specific hotel by using the Chain Code, the Brand Code, and the Hotel Code. The codes used are agreed upon by trading partners.
@HotelCode	1	The code that uniquely identifies a single hotel property. The hotel code is decided between vendors.
@ChainCode	0..1	A code that identifies the brand or flag of a hotel, often used for independently-owned or franchised properties who are known by a specific brand.
@BrandCode	0..1	The code that identifies a hotel chain or management group. The hotel chain code is decided between vendors. This attribute is optional if the hotel is an independent property that can be identified by the HotelCode attribute.
@HotelCodeContext	0..1	A text field used to communicate the context (or source of – ex Sabre, Galileo, Worldspan, Amadeus) the HotelReferenceGroup codes.
HTNG_DeviceStatusRQ / Devices	1	A collection of devices.
HTNG_DeviceStatusRQ / Devices / Device	1..n	Container element which holds information describing the device.
@Type	0..1	Specific classification of the device, i.e. Thermostat, SetTopBox, etc.
@ID	1	An identifier that is unique within the network.
@Class	0..1	General classification of the device, ie HVAC, TelevisionIntegration, etc.

Element @Attribute	Num	Description/Contents
HTNG_DeviceStatusRQ / Devices / Device / EndPointAddress	1	Unique endpoint address of this device.
HTNG_DeviceStatusRQ / Devices / Device / Action	1	A container element that wraps a given command.
@Type	1	Must be equal to "STATUS"
@Operation	1	The method/function that is being called.

4.7.2 Data Element Table – Response

Element @Attribute	Num	Description/Contents
HTNG_DeviceStatusRS	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceStatusRS / Success	0..1	The presence of the empty Success element explicitly indicates that the OpenTravel versioned message succeeded.
HTNG_DeviceStatusRS / Warnings	0..1	Used in conjunction with the Success element to define one or more business errors.
HTNG_DeviceStatusRS / Warnings / Warning	1..n	Used when a message has been successfully processed to report any warnings or business errors that occurred.

Element @Attribute	Num	Description/Contents
@Type	1	The Warning element MUST contain the Type attribute that uses a recommended set of values to indicate the warning type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_DeviceStatusRS / Errors	0..1	A collection of errors that occurred during the processing of a message.
HTNG_DeviceStatusRS / Errors / Error	1..n	An error that occurred during the processing of a message.
@Type	1	The Error element MUST contain the Type attribute that uses a recommended set of values to indicate the error type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.

Element @Attribute	Num	Description/Contents
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_DeviceStatusRS / Devices	1	A collection of devices
HTNG_DeviceStatusRS / Devices / Device	1..n	Container element which holds information describing the device.
@Type	0..1	Specific classification of the device, i.e. Thermostat, SetTopBox, etc.
@ID	1	An identifier that is unique within the network.
@Class	0..1	General classification of the device, ie HVAC, TelevisionIntegration, etc.
HTNG_DeviceStatusRS / Devices / Device / EndPointAddress	1	Unique endpoint address of this device.
HTNG_DeviceStatusRS / Devices / Device / Action	1	A container element that wraps a given command.
@Type	1	Must be equal to "STATUS"
@Operation	1	The method/function that is being called.
HTNG_DeviceStatusRS / Devices / Device / Action / Parameters	0..1	A collection of elements used to convey the parameters passed to the function call.
HTNG_DeviceStatusRS / Devices / Device / Action / Parameters / Parameter	1..n	A single parameter.
@Property	1	The name of the property.
@Key	0..1	The abstract display name corresponding to the Value.
@Value	1	The value of the Property

4.8 Interacting with Devices - Event

4.8.1 Data Element Table – Request

Element @Attribute	Num	Description/Contents
HTNG_DeviceEventRQ	1	Root element of the message.

Element @Attribute	Num	Description/Contents
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceEventRQ / POS	1	POS provides a mechanism to indicate the source of the message.
HTNG_DeviceEventRQ / POS / Source	1	This holds details regarding the requestor. It may be repeated to also accommodate the delivery systems.
HTNG_DeviceEventRQ / POS / Source / RequestorID	1	An identifier of the entity making the request (e.g., ATA/IATA/ID number, Electronic Reservation Service Provider (ERSP), Association of British Travel Agents (ABTA)).
@Type	0..1	A reference to the type of object defined by the UniqueID element. Refer to OpenTravel Code List Unique ID Type (UIT).
@ID	1	A unique identifying value assigned by the creating system. The ID attribute may be used to reference a primary-key value within a database or in a particular implementation.
@ID_Context	0..1	Used to identify the source of the identifier (e.g., IATA, ABTA).
HTNG_DeviceEventRQ / POS / Source / RequestorID / CompanyName	0..1	Identifies the company that is associated with the UniqueID.
@CompanyShortName	1	Used to provide the company common name.
HTNG_DeviceEventRQ / PropertyInfo	1	Identifies a specific hotel by using the Chain Code, the Brand Code, and the Hotel Code. The codes used are agreed upon by trading partners.

Element @Attribute	Num	Description/Contents
@HotelCode	1	The code that uniquely identifies a single hotel property. The hotel code is decided between vendors.
@ChainCode	0..1	A code that identifies the brand or flag of a hotel, often used for independently-owned or franchised properties who are known by a specific brand.
@BrandCode	0..1	The code that identifies a hotel chain or management group. The hotel chain code is decided between vendors. This attribute is optional if the hotel is an independent property that can be identified by the HotelCode attribute.
@HotelCodeContext	0..1	A text field used to communicate the context (or source of – ex Sabre, Galileo, Worldspan, Amadeus) the HotelReferenceGroup codes.
HTNG_DeviceEventRQ / Device	1	Container element which holds information describing the device.
@Type	0..1	Specific classification of the device, i.e. Thermostat, SetTopBox, etc.
@ID	1	An identifier that is unique within the network.
@Class	0..1	General classification of the device, ie HVAC, TelevisionIntegration, etc.
HTNG_DeviceEventRQ / Device / EndPointAddress	1	Unique endpoint address of this device.
HTNG_DeviceEventRQ / Device / Action	1	A container element that wraps a given command.
@Type	1	Must be equal to “EVENT”
@Operation	1	The method/function that is being called.
HTNG_DeviceEventRQ / Device / Action / Parameters	0..1	A collection of elements used to convey the parameters passed to the function call.
HTNG_DeviceEventRQ / Device / Action / Parameters / Parameter	1..n	A single parameter.
@Property	1	The name of the property.
@Key	0..1	The abstract display name corresponding to the Value.
@Value	1	The value of the Property

Element @Attribute	Num	Description/Contents
@PreviousValue	0..1	If known, the previous value of the property.

4.8.2 Data Element Table – Response

Element @Attribute	Num	Description/Contents
HTNG_DeviceEventRS	1	Root element of the message.
@EchoToken	1	A reference for additional message identification, assigned by the requesting host system. When a request message includes an echo token, the corresponding response message MUST include an echo token with an identical value.
@TimeStamp	1	Indicates the creation date and time of the message in UTC using the following format specified by ISO 8601; YYYY-MM-DDThh:mm:ssZ with time values using the 24-hour clock (e.g., 20 November 2003, 1:59:38 pm UTC becomes 2003-11-20T13:59:38Z).
@Version	1	For all OpenTravel versioned messages, the version of the message is indicated by a decimal value.
HTNG_DeviceEventRS / Success	0..1	The presence of the empty Success element explicitly indicates that the OpenTravel versioned message succeeded.
HTNG_DeviceEventRS / Warnings	0..1	Used in conjunction with the Success element to define one or more business errors.
HTNG_DeviceEventRS / Warnings / Warning	1..n	Used when a message has been successfully processed to report any warnings or business errors that occurred.
@Type	1	The Warning element MUST contain the Type attribute that uses a recommended set of values to indicate the warning type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type = "Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).

Element @Attribute	Num	Description/Contents
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).
HTNG_DeviceEventRS / Errors	0..1	A collection of errors that occurred during the processing of a message.
HTNG_DeviceEventRS / Errors / Error	1..n	An error that occurred during the processing of a message.
@Type	1	The Error element MUST contain the Type attribute that uses a recommended set of values to indicate the error type. The validating XSD can expect to accept values that it has NOT been explicitly coded for and process them by using Type ="Unknown". Refer to OpenTravel Code List Error Warning Type (EWT).
@Status	0..1	If present, recommended values are those enumerated in the OTA_ErrorRS, (NotProcessed Incomplete Complete Unknown) however, the data type is designated as string data, recognizing that trading partners may identify additional status conditions not included in the enumeration.
@ShortText	1	An abbreviated version of the error in textual format.
@Code	0..1	If present, this refers to a table of coded values exchanged between applications to identify errors or warnings. Refer to OpenTravel Code List Error Codes (ERR).

5 Appendices

5.1 Glossary of Terms

For the purpose of this document the following terms have been defined as follows:

Term	Definition
Device Capability Profile	A device profile defines a common set of capabilities supported by a particular class of device. A device profile makes it possible to maintain a single source of capability data that can be used to describe a large number of identical devices.
Device Discovery Requester	Any system interested in locating devices and their capabilities.
Device Discovery Responder	A repository of references (for the purpose of Addressing) to servers, systems, services and devices and their capabilities.
Device Registration Requester	A system or device capable of publishing device information to be made available to other systems or devices.
Device Registration Responder	A repository of references (for the purpose of Addressing) to servers, systems, services and devices and their capabilities.
Device Registration System	A repository of references (for the purpose of Addressing) to servers, systems, services and devices and their capabilities.
Discovery	A system that interacts with the Registration role to provide references to servers, systems, services and devices. Device Discovery utilities allow remote identification of the devices and create lists of the devices with relevant information. Its ultimate goal is to standardize and streamline the process of integration between applications and device services.
Endpoint	The IP network address of a device service. This is not to be confused with the physical address of a device.
Gateway	A system that acts as a proxy to other gateways, bridges or devices.
Hotel Information System	Any hotel software application or service containing features sets based on the status of guest room devices.
Intelligent Device	A piece of hardware that can be queried or changed, or report its state.
Device Control Publisher	Any device or system capable of monitoring and publishing device property changes.
Device Control Requester	Any hotel software application or service containing feature

	sets based on the status of guest room devices.
Device Control Responder	A device or system (acting on behalf of another device or system) that receives commands, responds to status queries or publishes events.
Device Control Subscriber	Any hotel software application or service interested in being notified of changes to properties occurring in a guest room device.
Device Registration Server	Stores information about devices and allows for the querying of device capabilities and how to address them.
Intelligent Guest Room (IGR) System Registration	A system that provides the ability to query the status of guest room devices. A process used to add a device to a UDDD registration system. The registration process involves defining the details (including endpoint) of all devices within the control span of the system/gateway/controller.
Room Status Publisher	A system that provides the ability to register for and publish events relating to the guest room devices.
Room Status Subscriber	A system interested in receiving real-time updates to the health and status of guest room devices.
Status Server	A type of gateway, capable of caching room device status/state and capable of monitoring and alerting.
Web Service	The W3C definition is “a software system designed to support interoperable machine-to-machine interaction over a network”.

5.2 Referenced Documents

The following table shows the documents upon which this document depends:

Document Title	Location/URL
HTNG Device Messaging Structure (DMS) Specification v2.0	http://collaboration.htng.org/specs/documents.php?action=show&dcat=39&qdid=25888
HTNG Guest & Room Status Messaging (GRSM) Specification v2.0	http://collaboration.htng.org/specs/documents.php?action=show&dcat=42&qdid=23699
HTNG Event Notification Specification v2.0	https://collaboration.htng.org/specs/documents.php?action=show&dcat=54&qdid=26570
HTNG Web Services Specification v2.0	https://collaboration.htng.org/specs/documents.php?action=show&dcat=25&qdid=22364
OpenTravel Alliance Specifications	http://opentravel.org/Specifications/Default.aspx